

H-1108  
310201842US1

Title of the Invention

RADIO-COMMUNICATION CONTROL METHOD AND EQUIPMENT

Inventors

Tsuyoshi TAMAKI,

Satoshi TAMAKI.

TITLE OF THE INVENTION

RADIO-COMMUNICATION CONTROL METHOD AND EQUIPMENT

FIELD OF THE INVENTION

5           The present invention relates to wireless access system and transmission system in radio-communication systems.

BACKGROUND OF THE INVENTION

10           In the conventional wireless access system, user terminals are connected to a wired network as represented by the wireless LAN via access points in order to enjoy the Internet services. In the existing wireless LAN, interference may be avoided through time multiplexing of the communication time between a plurality of user terminals and  
15           access points with a structure of carrier sense provided to detect communication devices which are making communication using the common frequency band but here rises a problem that since amount of data which can be transmitted in the unit  
20           time does not increase, the throughput of the entire system does not increase even when the number of access points is increased and thereby the throughput of an access point is lowered.

          The JP-B No.180775/2002 (U.S.P. No. 10/449100) filed  
25           previously provides a structure to increase the throughput

of the entire system by simultaneously making communication among a plurality of access points as a measure to solve the problem described above.

Fig. 1 is an explanatory diagram of the method for  
5 improving the throughput with parallel transmissions among access points. In this figure, the access points 101a, 101b, and 101c are simultaneously making communications with user terminals 102a, 102b, and 102c. In this case, the simultaneous communications are realized by controlling the  
10 service area of the access point 101a so that the radio wave of the data transmitted from the access point 101a is not detected with a carrier sense of the access point 101b. The radio wave is not detected with a carrier sense under the condition that the power of the radio wave transmitted from  
15 the access point 101a goes lower than the reference received power preset in the access point 101b (hereinafter, referred to as a carrier sense threshold).

Similarly, the JP-B No. 180775/2002 provides a structure to control the service areas among the access  
20 points for parallel transmissions so that the radio wave transmitted from the access point 101b is not detected with a carrier sense of the access point 101c.

In the wireless access system described above, a structure to control the operations in order to satisfy the

condition to simultaneously transmit data communication packets is described but this wireless access system does not refer to a problem that the packets transmitted are not correctly received because of interference of the other data communications and are sometimes discarded.

Fig. 2 is an explanatory diagram of signal pair interference power ratio in the wireless access system. The access point 101a transmits data packet in the transmission power  $AP1\_TXP$  and the user terminal 102a receives the desired signal in the received power  $AP1\_STA1\_RXP$ . Moreover, the user terminal 102a receives the signal, which has been transmitted from the access point 102a as the data packet to the user terminal 102b in the transmission power  $AP2\_TXP$ , as the interference signal in the received power  $AP2\_STA1\_RXP$ . In this timing, a power ratio of the desired signal and the interference signal becomes equal to the signal pair interference power ratio. Although, depending on the demodulation performance of a receiver, when the signal pair interference power ratio  $SIR$  is equal to or higher than the desired signal pair interference power ratio  $SIR\_req$ , the data signal is demodulated correctly, but if it is equal to or lower than the desired signal pair interference power ratio  $SIR\_req$ , the data signal is demodulated erroneously due to the collision of packets.

Fig. 3 is a graph showing an example of geographical distribution of the signal pair interference power ratio SIR. This figure indicates amplitudes of signal pair interference power ratios (SIRs) when the receiving places are changed in the data communication performed between both access points with the same radio-communication channel in the equal transmission power in the case where a room of 10 m square is assumed and the access point 101a and access point 101b are provided to the corners of this room. When the desired signal pair interference power ratio  $SIR_{req}$  is assumed as 10 dB, the predetermined signal pair interference power ratio  $SIR_{req}$  may be satisfied within the range of 4 m around the access points even when the communications are simultaneously conducted by abovementioned two access points. The domain in which the predetermined signal pair interference power ratio  $SIR_{req}$  is satisfied is hereinafter referred to as the non-interference domain. In the domain isolated by 4m or more away from the access point, the predetermined signal pair interference power ratio  $SIR_{req}$  cannot be satisfied. This domain is hereinafter referred to as the interference domain. When two access points described above make communications simultaneously to the user terminals in this interference domain, here rises a problem that data is lost due to the collision of packets.

## SUMMARY OF THE INVENTION

For the purpose of improving the throughputs of user terminals in the non-interference domain, the present invention provides, in order to solve the problems described  
5 above, a wireless access system to control deterioration of the throughput due to collision of data packets in which the simultaneous communications are performed from a plurality of access points to the user terminals in the non-interference domain and the time-divided  
10 communications are performed from carrier senses to user terminals in the interference domain, utilizing a means to judge whether the user terminals associated with the access points are in the interference domain or in the non-interference domain and a means for time division of the  
15 transmission time from the access points to the user terminals in the non-interference domain and the user terminals in the interference domain.

In more practical, an access point is provided with a means for periodically transmitting a beacon signal, a  
20 means for measuring received power of the beacon signal of the other access point, a means for notifying the measured received power and the preset transmission power of beacon signal, a means for transmitting the preset transmission timing and transmission power designated for each user

terminal, and a means for synchronization of time for simultaneous transmissions from a plurality of access points. Moreover, a user terminal is provided with a means for measuring the received power of beacon signal of the access point and a means for notifying the measured received power information. In addition, an apparatus for integrated management of data communications at a plurality of access points (hereinafter, referred to as a management server) is also provided. This management server is provided with a means for collecting the received power information of the beacon signal and the transmission power information of the beacon signal measured at the access point and user terminal, a means for judging whether the user terminal is in the interference domain or in the non-interference domain using the collected information, a means for calculating the data transmission timing for user terminals in the interference domain and user terminals in the non-interference domain, a means for calculating the transmission power for each user terminal, a means for notifying the calculated transmission timing and transmission power to the access points, and a means for generating the signal for synchronizing the access points for simultaneous communications at a plurality of access points. The system is comprised of the apparatuses described above and thereby there is provided a wireless

access system to improve the throughput of entire system  
through elimination of collision of data packets and control  
of deterioration of throughput of user terminals in the non-  
interference domain by dividing with time the transmitting  
5 time to the user terminals in the non-interference domain  
and user terminals in the interference domain.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is an explanatory diagram of a throughput  
10 improving method through parallel transmissions at access  
points in a wireless access system;

Fig. 2 is an explanatory diagram of signal pair  
interference power ratio in the wireless access system;

Fig. 3 is a graphic diagram indicating an example of  
15 geographical distribution characteristic of the signal pair  
interference power ratio;

Fig. 4 is an explanatory diagram of a time dividing  
method of transmission time to user terminal in the  
preferred embodiment of the present invention;

20 Fig. 5 is a system structural diagram in the preferred  
embodiment of the present invention;

Fig. 6 is a control sequence diagram in the preferred  
embodiment of the present invention;

Fig. 7 explains database information for transmitting control such as (1) access point setting information, (2) received power information of beacon signal of access points, (3) received power information of beacon signal of user terminals, and (4) traffic information of access points (downlink) in the preferred embodiment of the present invention;

Fig. 8 is an algorithm (Part 1) of transmitting control information calculation in the preferred embodiment of the present invention;

Fig. 9 is an algorithm (Part 2) of transmitting control information calculation in the preferred embodiment of the present invention;

Fig. 10 is an algorithm (Part 3) of transmitting control information calculation in the preferred embodiment of the present invention;

Fig. 11 is an explanatory diagram of a transmitting control signal in the preferred embodiment of the present invention;

Fig. 12 is an explanatory diagram of a transmission control part of an access point in the preferred embodiment of the present invention;

Fig. 13 is a graphic diagram for evaluation of throughput in the preferred embodiment of the present invention; and

Figs. 14A and 14B are graphical diagrams of the effect  
5 at the time of two parallel transmissions and the probability of non-interfering in the former method and the invention method.

#### DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

10 The preferred embodiment of the present invention will be described with reference to the accompanying drawings.

Fig. 4 is an explanatory diagram of a time dividing method of transmitting time for each user terminal in the  
15 preferred embodiment of the present invention. There is described an example of data transmissions to user terminals 102a and 102c from an access point 101a and to user terminals 102b and 102d from an access point 101b. Here, it is assumed that the user terminals 102a and 102b are provided in the  
20 non-interference domain, while the user terminals 102c and 102d in the interference domain. First, there is described an example of simultaneous communications to the user terminals 102a and 102b provided in the non-interference domain from the access points 101a and 101b. The time

required for simultaneous communications is hereinafter referred to as transmission time for all AP to user terminals in non-interference domain  $T_{\text{noint}}$ . Since the predetermined signal pair interference power ratio  $SIR_{\text{req}}$  is satisfied at user terminals within the transmission time for all AP to user terminals in non-interference domain  $T_{\text{noint}}$  even when the simultaneous communications are performed at a plurality of access points, each access point makes communication by invalidating carrier sense thereof.

10       Next, there is also described an example of communications between the access point 101a and the user terminal 102a in the non-interference domain and between the access point 101b and the user terminal 102d in the interference domain. This communication time is referred to as the transmission time for AP1 to user terminals in non-interference domain  $T_{\text{AP1}}$ . In this transmission time for AP1, since it is probable that packets will collide with each other at the user terminal 102d due to an interference signal from the access point 101a, the carrier sense of the access point 101b is validated, while the carrier sense of the access point 101a is kept invalidated.

Subsequently, there is described an example of communications between the access point 101a and the user terminal 102c in the interference domain and between the

access point 101b and the user terminal 102b in the non-interference domain. This communication time is referred to as the transmission time for AP2 to user terminals in non-interference domain  $T_{AP2}$ . In this transmission time  
5 for AP2, the carrier sense of the access point 101a is validated, while the carrier sense of the access point 101b is kept invalidated.

Finally, there is described an example of communications between the access point 101a and the user  
10 terminal 102c in the interference domain and between the access point 101b and the user terminal 102d in the interference domain. In this case, communication is performed with the CSMA/CA system or the like between each access point and each user terminal. This communication  
15 time is referred to as the random access time  $T_{rnd}$ . In this case, the carrier senses of both access points 101a and 101b are validated.

Fig. 5 is a system structural diagram in the preferred embodiment of the present invention. The system of Fig. 5  
20 is comprised of the access point 101a, the user terminal 102a and a management server 501 for management of access points. However, the management server 501 is assumed to be able to conducting management of a plurality of access points and user terminals.

The management server 501 comprises a synchronous signal generator 502 for generating a synchronous signal getting the timing of simultaneous communications at a plurality of access points, a wired interface signal  
5 processing part 505 for making communication with a plurality of access points, a database for transmission control 504 for collecting the beacon signal received power information and the beacon signal transmission power information measured at a plurality of access points and  
10 user terminals, and a transmitting control information calculation part 503 for calculating the data transmission timing, using the database 504 for transmission control, for the user terminals in the interference domain and user terminals in the non-interference domain and the  
15 transmission power to each user terminal and then notifying the calculated transmission timing and transmission power to the access points.

The access point 101a comprises a wired interface signal processing part 506 for making communication with the  
20 management server 501, a beacon signal generator 508 for periodically transmitting the beacon signal which is required to check the radio wave transmission condition in the transmission link for access points or user terminals, a radio transmitter 511 for transmitting the radio signal  
25 by encoding and modulating the transmission signals such as

beam signal and data signal to realize errorless communication through the radio transmission link, a radio receiver 512 for demodulating and decoding the received radio signal to the original signal, a measurement  
5 information transmission part 510 for measuring the received power of the beacon signal from the other access points and then transmitting, to the management server 501, the beam transmission power, carrier sense threshold, and the measured beacon received power preset in the access  
10 point, a transmission control part 509 for transmitting the user data by setting the transmission timing and transmission power designated from the transmitting control information calculation part 503 for each user terminal, and a synchronous timer 507 for controlling the timing of the  
15 transmission control part or the like in synchronization with the synchronous signal generated by the synchronous signal generator 502 of the management server 501 for the simultaneous transmissions at a plurality of access points.

The user terminal 102a comprises a radio receiver 513  
20 for receiving the radio signal from access points, a received power measurement part 515 for measuring the received power of beacon signal of access points, and a radio transmitter 514 for transmitting the radio signals such as result of measurement of received power and data signal to

access points. The result of measurement of received power is notified to the management server 501 via access points.

As the flow of control signal, the measurement information is collected to database 504 for transmission control of the management server 501 from the measurement information transmission part 510 of the access point 101a and the received power measurement part 515 of the user terminal 102a and the transmitting control information calculation part 503 calculates the transmission timing and transmission power for each terminal to the transmission control part 509 using this database for transmission control 504 and thereafter notifies these calculated data to the relevant access point. The transmission control part 509 controls operations to make communication in the transmission timing and transmission power designated for the user data signal.

Fig. 6 is a control sequence diagram in the preferred embodiment of the present invention. First, the access point 101a transmits the access point setting values such as transmission power of beacon signal and carrier sense threshold value to the management server 501 as the access point setting information. Moreover, the access point 101a measures the received power of beacon signal transmitted from the other access point 101b and then notifies this

received power to the management server 501 as the received power information of beacon signal. In addition, the access point 101a notifies the traffic information to user terminal from access point (down-link traffic information) to the management server 501. The user terminal 102a provided within the cell of access point 101a to receive the data from the access point 101b receives the beacon signals of the access points 101a and 101b, measures the received power, and notifies the measured power to the management server 501 as the received power information of beacon signal.

The management server 501 records the notified information to the database for transmission control 504 and calculates, based on this recorded information, the transmitting control information the transmission timing and transmission power of the data packet to the user terminal 102a from the access point 101a. The result of calculation is notified to the access point 101a as the transmitting control signal. Like the access point 101a, the transmitting control signal is also notified to the access point 101b. The access point 101a transmits the user data to the user terminal 102a in the designated transmission timing and transmission power.

Fig. 7 explains database information for transmitting control in the preferred embodiment of the present

invention. The database for transmitting control comprises the access point setting information (1) indicating the transmission power of beacon signal ( $APi\_Btxp$ ) and carrier sense threshold ( $APi\_CSthr$ ) at each access point  $APi$ , the  
5 received power information (2) of beacon signal ( $APi\_APj\_Brxp$ ) from the other access point  $APi$  of the access point  $APj$ , the received power information (3) of beacon signal ( $APi\_STAj\_Brxp$ ) from the access point  $APi$  of the user terminal  $STAj$ , and the traffic information ( $APi\_STAj\_TRA$ )  
10 to the user terminal  $STAj$  from the access point  $APi$  (downlink). With the control sequence of Fig. 6, the information pieces described above are collected from a plurality of access points and user terminals.

As the embodiment of a method of measuring the traffic  
15 information ( $APi\_STAj\_TRA$ ) of the access point  $APi$ , the traffic entering the queue of a transmitting buffer of the transmission control part 509 may be used as the amount of information per unit time. As the other embodiment, the average length of queue of the transmitting buffer of the  
20 transmission control part 509 may be used as the traffic information.

Fig. 8, Fig. 9, and Fig. 10 illustrate algorithms of transmitting control information calculation in the preferred embodiment of the present invention.

The algorithm of transmitting control information calculation can be roughly classified into following three steps.

Step 1: The predetermined transmission power to the  
5 terminals STA<sub>j</sub> associated with each access point AP<sub>i</sub> is calculated.

Step 2: It is judged whether the user terminal STA<sub>j</sub> associated with each access point AP<sub>i</sub> is in the interference domain or in the non-interference domain and traffics in the  
10 non-interference domain and interference domain area compared with each other. For instance, a rate of the number of user terminals in the non-interference domain or a rate of traffic to the number of user terminals in the non-interference domain (hereinafter, referred to as  
15 probability  $P_i$  of non-interfering) is calculated.

Step 3: Using the probability  $P_i$  of non-interfering obtained in the step 2, the transmission timing information of the access point AP<sub>i</sub> described in Fig. 4 (transmission time for all AP to user terminals in non-interference domain  
20 T<sub>noint</sub>, transmission time for AP<sub>i</sub> to user terminals in non-interference domain T<sub>APi</sub>, transmission time for AP<sub>j</sub> to user terminals in non-interference domain T<sub>APj</sub>, random access time T<sub>rnd</sub>) is calculated.

Details of each step will be described below with reference to the accompanying drawings.

The step 1 will be described with reference to Fig. 8. Only one access point  $AP_i$  is selected and the  
5 predetermined transmission power  $AP_i\_STA_j\_Dtxp$  of the user data to the user terminal  $STA_j$  associated with the access point  $AP_i$  is calculated with the formula 1.

[Formula 1]

$$AP_i\_STA_j\_Dtxp = (AP_i\_Btxp - AP_i\_STA_j\_Brxp) + Min\_Drxp + \alpha$$

10 Here, each symbol is assumed to have following meaning.

- $AP_i\_Btxp$ : Transmission power of beacon signal of the access point  $AP_i$  (value read from the database for transmitting control)
- 15 -  $AP_i\_STA_j\_Brxp$ : Received power of beacon signal when the user terminal  $STA_j$  has received the beacon signal of the access point  $AP_i$  (value read from the database for transmitting control)
- $Min\_Drxp$ : Minimum received power required for  
20 correct decoding and demodulation of user data (fixed value)
- $\alpha$  : Margin for variation of received power (fixed value)

The predetermined transmission power is obtained using the formula 1 for all access points. Here, transmission is not performed with unnecessarily higher transmission power in view of reducing interference on the  
5 other communications as much as possible.

The step 2 will then be described with reference to Fig. 9. Only one access point  $AP_i$  is selected and the signal pair interference power ratio  $SIR_j$  of the user terminal  $STA_j$  associated with the access point  $AP_i$  is obtained from the  
10 formula 2.

[Formula 2]

$$SIR_j = 10 \log \frac{10^{(AP_i\_Btxp - AP_i\_STAj\_Brxp)/10}}{\sum_{k \neq i} 10^{(AP_k\_Btxp - AP_k\_STAj\_Brxp)/10}}$$

Next, the universal set of user terminals associated with the access point  $AP_i$  is designated as  $U$ , while a set  
15 of user terminals in which the signal pair interference power ratio  $SIR_j$  of the user terminal  $STA_j$  is equal to the predetermined signal pair interference power ratio  $SIR_{req}$  or higher. In this case, the probability of non-interference  $P_i$  may be obtained from any one of the  
20 formulae 3 and 4.

[Formula 3]

$$P_i = Num\_S / Num\_U$$

[Formula 4]

$$P_i = \sum_{j \in S} A_{Pi\_STAj\_TRA} / \sum_{j \in U} A_{Pi\_STAj\_TRA}$$

Here, each symbol is assumed to have the following  
5 meaning.

- Num\_S: Number of user terminals of the set S of user terminals in which the signal pair interference power ratio SIR<sub>J</sub> of the user terminal STA<sub>j</sub> is equal to the predetermined signal pair interference power ratio SIR<sub>req</sub> or higher  
10 (obtained from the database for transmitting control)
- Num\_U: Number of user terminals of the universal set U of user terminals associated with the access point A<sub>Pi</sub> (obtained from the database for transmitting control)
- A<sub>Pi\\_STAj\\_TRA</sub>: Traffic information to the user terminal  
15 STA<sub>j</sub> from the access point A<sub>Pi</sub> (read from the database for transmitting control)

The probability of non interference P<sub>i</sub> is also obtained for the other access points.

The step 3 will be described with reference to Fig.  
20 10. In order to classify the transmission time into the time for simultaneous communications of a plurality of access

points and the time for communications by random access, it is required that a plurality of access points are considered as one group and the timings for various communications of all access points within the same group must be placed under  
5 the adequate management. The group of such access points is designated as a set of access points which carry out mutual interference. Only one access point  $AP_i$  is selected and a set  $J$  of access points  $AP_j$  satisfying the formula 5 for the access point  $AP_i$  (set of access points which carry  
10 out mutual interference) is obtained.

[Formula 5]

$$(AP_j\_Btxp - AP_j\_AP_i\_Brxp) \geq AP_i\_CSthr$$

Here, each symbol is assumed to have following meaning.

- 15 -  $AP_j\_Btxp$ : Transmission power of beacon signal of the access point  $AP_j$  (read from the database for transmitting control)
- $AP_j\_AP_i\_Brxp$ : Received power of beacon signal which has been transmitted from the access point  $AP_j$  and received by  
20 the access point  $AP_i$  (read from the database for transmitting control)

- APi\_CStthr: Carrier sense threshold of the access point APi (read from the database for transmitting control)

Next, using the probability  $P_i$  of non-interference of the access point APi obtained previously and probability  $P_j$  of non-interfering of the access point  $P_j$  associated with a set of access points which carry out mutual interference, the transmission time for all AP to user terminals in non-interference domain  $T_{\text{noint}}$ , the transmission time for APi to user terminals in non-interference domain  $T_{\text{APi}}$ , the transmission time for APj to user terminals in non-interference domain  $T_{\text{APj}}$ , and the random access time  $T_{\text{rnd}}$  are obtained as the transmission timing control information from the formulae 6, 7, 8, and 9.

[Formula 6]

$$T_{\text{noint}} = P_i \times \prod_{j \in J} P_j$$

[Formula 7]

$$T_{\text{APi}} = P_i \times \prod_{j \in J} (1 - P_j)$$

[Formula 8]

$$T_{\text{APj}} = P_j \times (1 - P_i) \times \prod_{k(\neq j) \in J} (1 - P_k)$$

[Formula 9]

$$T\_rnd = 1 - T\_noint - T\_APi - \sum_{j \in J} T\_APj$$

In the other embodiment, the non-interference transmission time  $T\_noint$  and the random access time  $T\_rnd$  are obtained from the formulae 10 and 11 under the condition that the transmission time for  $APi$  to user terminals in non-interference domain  $T\_APi$  and transmission time for  $APj$  to user terminals in non-interference domain  $T\_APj$  are set to 0.

10 [Formula 10]

$$T\_noint = \min_{j \in J} \{Pi, Pj\}$$

[Formula 11]

$$T\_rnd = (1 - T\_noint)$$

However, the transmission time for all AP to user terminals in non-interference domain or the like of the above formula has been normalized with the control frame time. The transmission timing obtained with the formulae 6, 7, 8, and 9 or 10, and 11 is notified as the transmitting

15

control signal to the access point APi with addition of the transmission power information obtained from the formula 1.

The processes described above are performed to all access points.

5            Fig. 11 is an explanatory diagram of the transmitting control signal from a management server to an access point in the embodiment of the present invention. One control frame time  $T_{\text{frame}}$  means a time duration to generate down-link traffic to the terminal to which the access point  
10 APi belongs. Transmission is performed to the terminals in the non-interference domain in the transmission time for all AP to user terminals in non-interference domain  $T_{\text{noint}}$ . The number of interference access points  $AP_{\text{num}}$  is notified and the ID (address or the like)  $AP_{\text{ID}}$  of the access points  
15 APi as many as  $AP_{\text{num}}$  and each transmission time for APi to user terminals in non-interference domain  $T_{\text{APi}}$  are also notified. Within the set of the identical interference access points, the transmission sequence can be maintained among a plurality of access points by arranging the access  
20 point IDs in the ascending order. The transmission sequence is maintained among a plurality of access points. When elements of the set of interference access points of access point AP1 are different from that of the set of interference access points of access point AP2, the access points which

will become the common elements are grouped first and the access points of different elements are grouped subsequently to keep the ascending order of the access point ID within the group.

5           The access point  $AP_i$  is capable of transmitting the user data to the terminals within the non-interference domain during the transmission time for  $AP_i$   $T_{AP_i}$  and also transmits this data to the terminals in the interference domain during the other period. In the random access time  
10  $T_{rnd}$ , the user data can be transmitted to the user terminals within the interference domain.

          The number of terminals under the management of access points is notified with the number of user terminals  $STA\_Num$ . The SIR which suggests the judgment criterion for  
15 the user terminals within the interference domain or in the non-interference domain with the predetermined signal pair interference power ratio  $SIR_{req}$ . The terminal ID ( $STA\_ID$  such as address), the signal pair interference power ratio  $SIR_j$  obtained from the formula 2, and the predetermined  
20 transmission power  $AP_i\_STA_j\_Dtxp$  obtained from the formula 1 are notified. Otherwise, it is also allowed that the result of judgment by the management server to detect each user terminal existing in the non-interference domain or in the interference domain is notified in the form of a graph,

in place of notifying the predetermined signal pair  
interference power ratio  $SIR_{req}$  and the signal pair  
interference power ratio  $SIR_j$  at each user terminal. The  
access point  $AP_i$  controls each user terminal as illustrated  
5 in Fig. 11 depending on the notified transmission timing and  
the transmission power.

Fig. 12 illustrates an example of structure of the  
transmission control part of access point in the embodiment  
of the present invention. The transmission control part has  
10 the function to set the transmission timing and transmission  
power to each user terminal in accordance with the  
transmitting control signal from the management server.

First, when the user data packet reaches the  
transmission control part, a transmission queue  
15 distributing part 1201 distributes the packets to the  
transmission queues 1202a, 1202b, 1202c by reading the  
destination address of packets. Distribution to the  
transmission queue may be realized with the following two  
kinds of methods.

- 20 - Method for assigning one by one the user terminals to the  
transmission queue 1:
- Method for collecting the user terminals, satisfying the  
predetermined signal pair interference power ratio  $SIR_{req}$   
with the signal pair interference power ratio  $SIR_j$ , to the

transmission queue 1 and collecting the terminals, not satisfying the predetermined signal pair interference power ratio  $SIR_{req}$ , to the other transmission queue:

When the number of packets is counted in these  
5 transmission queues, the result may be used for obtaining the traffic information to the user terminals from the access points and the rate of communications between the non- interference domain and the interference domain.

Next, a transmission time control part 1203 extracts  
10 packets from the transmission queue depending on the designated transmission timing information. A synchronous timer 507 is set for synchronous interruption based on the information of one control frame time  $T_{frame}$ , transmission time for all AP to user terminals in non-interference domain  
15  $T_{noint}$ , transmission time for  $AP_i$  to user terminals in non-interference domain  $T_{APi}$ , transmission time for  $AP_j$  to user terminals in non-interference domain  $T_{APj}$ , and random access time  $T_{rnd}$  and the packets can be extracted from the transmission queue assigned to the user terminals for non-  
20 interference domain in the case of the transmission time for all AP to user terminals in non-interference domain  $T_{noint}$  and transmission time for  $AP_i$  to user terminals in non-interference domain  $T_{APi}$  when the interruption occurs.

A transmission power setting part 1204 sets the predetermined transmission power  $API\_STAj\_Dtxp$  for the user terminal  $STAj$  to a radio transmitter 511.

5 A retransmission control part 1205 stores the packet transmitted to the radio transmitter 511 within a transmission buffer 1206 and waits for reception, from the radio receiver 512, of a message suggesting that the data arrival response packet Ack from the user terminal. When Ack time-out occurs earlier after the Ack waiting time is  
10 set to the synchronous timer 507, the retransmission control packet is also transmitted depending on the transmission timing by returning the packet stored in the transmission buffer 1206 to the transmission queue distributing part 1201.

15 Here, it is also possible to form the structure in which a plurality of access points under the management of the management server are connected to the network via the management server. In this case, the traffic information and rate of communications between the non-interference  
20 domain and the interference domain can be detected in direct in the management server and thereby traffic of the control information between the management server and each access point can be reduced. Even in this case, detection of transmission link condition among the access points and

between the access point and user terminal and control of timing for data transmission and transmission power can be performed in the same manner.

According to the present invention, the total  
5 throughput of the system can be improved, in the wireless access system, through time division of the transmission timing of access points not to eliminate collision of data packet for the user terminals which receive simultaneously the data packets transmitted simultaneously from a  
10 plurality of access points and cannot correctly demodulate the predetermined signal due to the collision of data packets and through the simultaneous transmission of transmission timing of access points for the user terminals which can correctly demodulate the predetermined signal  
15 when the signal pair interference power ratio is large even if collision of the data packets occurs.

Fig. 13 illustrates a graph indicating the result of evaluation of throughput in the preferred embodiments of the present invention.

20 During the transmission time for all AP to user terminals in non-interference domain, the access point 101a is transmitting the data to the user terminal 102a, while the access point 101b, to the user terminal 102b. Since both user terminals 102a and 102b exists within the

non-interference domain, it can be understood that the throughput is 6 Mbps or higher.

During the transmission time for AP1 to user terminals in non-interference domain, the access point 101a is  
5 transmitting the data to the user terminal 102a, while the access point 101b, to the user terminal 102d. Although the terminal 102a transmits the data of 6 Mbps or higher, the data communication rate is deteriorated to about 3 Mbps due to the collision of data packets from the access point 101a  
10 because the terminal 102d exists within the non-interference domain.

During the transmission time for AP2 to user terminals in non-interference domain, the access point 101a is transmitting the data to the user terminal 102c, while the  
15 access point 101b, to the user terminal 102b. In this time, the terminal 102c is transmitting the signal in the rate of about 3 Mbps, while the terminal 102b, in the rate of about 6 Mbps or higher with the similar reason.

During the random access time, the access point 101a  
20 is transmitting the data to the user terminal 102c, while the access point 101b, to the user terminal 102d. Since both terminals are in the non-interference domain, the transmission rate of both terminals 102c and 102d is about 3 Mbps.

Figs. 14A and 14B illustrate the graphs regarding the effect of the embodiments of the present invention.

Probability P1 of non-interference of the access point 101a and probability P2 of non-interference of the access point  
5 101b are designated as the same value P in order to evaluate the throughput of the total system. Since the access point 101a and the access point 101b have been operated with the fixed transmission power in the prior art, the transmission timing has been divided with time using the carrier sense.  
10 Therefore, the throughput of system has been about 6 Mbps. In the present invention, however, the throughput can be raised up to about 12 Mbps which is equal to two times the throughput when the value of probability of  
non-interference is one (1). When the number of access  
15 points increases, the effect proportional to the number of access points can be obtained when the value of probability of non-interference is one (1).